

marantz®



SR4003 AV Receiver

The SR4003 introduces the new range of Marantz AV Receivers in the M1 design. The high-quality 7.1 PCM decoder, combined with the HDMI repeater function, makes it possible to enjoy the HD audio from Blu-ray Disc™. Its solid power supply, feeding the ultra stable 7x 80 Watts 8 ohms rms power amplifier, easily keeps control of the connected speaker, which – thanks to the OSD and Marantz's own MRAC auto set-up – has never been easier to set-up,. You also get a wide variety of analogue and digital video and audio inputs, outputs, including HDMI and Component video switching. All in all, it's an outstanding combination of home theatre receiver performance, top-quality features, and a highly versatile remote.



because music matters

marantz®



FEATURES	SR4003	OTHERS	
MULTICHANNEL SURROUND			
THX Ultra II / Select II	-	Auto speaker setup by microphone	M-RAC
THX Surround EX	-	Video conversion	CVBS < S > Comp
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	-/o/o/o	Video scaling	-
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIx	-/-/o/o	Videoprocessing	-
7.1 PCM for HD-Audio from BluRay and HD-DVD	o	T.B.C. - time base correction	-
Circle Surround II / Neural Surround	o/-	Front panel cursor control	o
Virtual Surround / Multichannel Stereo	o/o	On Screen Display: GUI / OSD / multiroom OSD	-/o/-
HT-EQ / Re-EQ	o/-	Variable cross over	5
		Lip sync control	-
		Multiroom zones	-
		Balanced in/out	-
		Front Flap	-
		Tuner	o
		Auto TV Switching (On/Off)	o
		Discrete RC coding (Main- / Multiroom)	-
		RS232C (control / update)	-/-
		VIDEO	-
		Composite In/Out	4/2
		S-Video In/Out	4/2
		Component In/Out	3/1
		HDMI in/out (version x.x)	2/1 (v1.1)
		HDMI V1.3 Deep Color pass through	-
		Multi-Room Video Out: Video / S-Video / Component	-/-/-
		AUDIO	-
		Analogue In/out	6/3
		Digital Optical In/Out	2/1
		Digital Coaxial In/Out	2/-
		Digital audio by HDMI	o
		Multi-Room Out: analog / digital	-/-
		7.1ch Pre Out / Main In	o/-
		7.1 multichannel input	o



OTHER	
Speaker Terminal: Gold plated screw / regular screw	-/o
Number of terminals	7
Speaker A/B	-
Bi-amp drive (5.1 ch setting) / Speaker C	-/-
Multi-Room Speaker Terminal	-
Multi-Room D.Bus	-
D.Bus	o
IR Receiver In / Emitter Out	-/-
IR Flasher In	-
RS232C	-
DC Triggers	-
Front Inputs: Audio / Composite / S-Video / Digital (Opt)	o/o/o/o
I-Pod input (direct / docking station)	-/o
USB Audio (MP3,AAC,WMA,WAV)	-

SPECIFICATIONS	
Power Output (8/6 Ohm RMS) (20Hz-20kHz 0.08%)	80/105 W
70% Guarantee	o
Audio Signal to Noise Ratio	105 dB
FM Tuner	o
Component video frequency response	5Hz to 80MHz (+-1dB)

GENERAL	
Available colors: Gold/Silver/Black/Silver-Gold	-/-/o/o
Metal Front Panel	o
System Remote Control	RC004SR
Pre-programmed / Learnable / Touch Screen	o/o/-
Multiroom remote (included / optional)	-/-
Power Consumption in W	500
Standby Consumption in W (normal/economy mode)	0.9/0.5
Detachable Power Cable	o
Maximum Dimensions (W x D x H) in mm	440x388x160.5
Weight in kg	11.6

Design and specifications are subject to change by Marantz without notice.