

marantz®



SR6003 AV Receiver

The SR6003 is the latest in the line of Marantz high-performance AV Receivers. It provides 7x100W / 8 ohms amplification, and comes with a vast array of features including i-Chips video conversion and scaling up to 1080p, Deep Color HDMI (three in and two outs), Dolby TrueHD and DTS HD Master Audio Decoder. The front panel 'with flap' design conceals all the buttons, including front inputs. There's also a USB input for your MP3 and WMA files: the inbuilt M-DAX ensures they sound great. Set-up is easy, thanks to the Graphical User Interface, the one-push Room Calibration by Audyssey MULT EQ, and the programmable LCD remote with backlight makes it a pleasure just to press 'on'.



because music matters

marantz®



FEATURES		OTHERS		OTHER	
MULTICHANNEL SURROUND					
THX Ultra II / Select II	-	Auto speaker setup by microphone	Audyssey MultEQ	Speaker Terminal: Gold plated screw / regular screw	-/o
THX Surround EX	-		CVBS <> S < > Comp >HDMI	Number of terminals	9
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	o/o/o/o/o	Video conversion		Speaker A/B	o
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIx	o/o/o/o/o	Video scaling	>1080p	Bi-amp drive (5.1 ch setting) / Speaker C	o/o
7.1 PCM for HD-Audio from BluRay and HD-DVD	o	Videoprocessing	i-Chips	Multi-Room Speaker Terminal	-
Circle Surround II / Neural Surround	o/o	T.B.C. - time base correction	o	Multi-Room D.Bus	-
Virtual Surround / Multichannel Stereo	o(Dolby VS)/o	Front panel cursor control	o	D.Bus	o
HT-EQ / Re-EQ	o/-	On Screen Display: GUI / OSD / multiroom OSD	o/o/-	IR Receiver In / Emitter Out	-/-
Dolby Headphone / TruSurround Headphone	o/-	Variable cross over	7	IR Flasher In	1
M-DAX Compressed audio Enhancer (MP3, WMA, ACC, iPod)	o	Lip sync control	o	RS232C	o
		Multiroom zones	1x ana / 1x dig	DC Triggers	1
		Balanced in/out	-	Front Inputs: Audio / Composite / S-Video / Digital (Opt)	o/o/o/o/o
		Front Flap	o	I-Pod input (direct / docking station)	-/o
		Tuner	o	USB Audio (MP3,AAC,WMA,WAV)	o
		Auto TV Switching (On/Off)	o		
		Discrete RC coding (Main- / Multiroom)	o		
		RS232C (control / update)	o/o		
		VIDEO	-		
		Composite In/Out	4/2	SPECIFICATIONS	
		S-Video In/Out	4/2	Power Output (8/6 Ohm RMS) (20Hz-20kHz 0.08%)	100/120 W
		Component In/Out	3/2	70% Guarantee	o
		HDMI in/out (version x.x)	3/2 (v1.3a)	Audio Signal to Noise Ratio	105 dB
		HDMI V1.3 Deep Color pass through	o	FM Tuner	o
		Multi-Room Video Out: Video / S-Video / Component	-/-/-	Component video frequency response	5Hz to 80MHz (+-1dB)
		AUDIO	-		
		Analogue In/out	6/3	GENERAL	
		Digital Optical In/Out	3/1	Available colors: Gold/Silver/Black/Silver-Gold	-/-/o/o
		Digital Coaxial In/Out	2/-	Metal Front Panel	o
		Digital audio by HDMI	o	System Remote Control	RC003SR
		Multi-Room Out: analog / digital	1/1	Pre-programmed / Learnable / Touch Screen	o/o/-
		7.1ch Pre Out / Main In	o/-	Multiroom remote (included / optional)	-/o
		7.1 multichannel input	o	Power Consumption in W	600
				Standby Consumption in W (normal/economy mode)	0.7/0.4
				Detachable Power Cable	o
				Maximum Dimensions (W x D x H) in mm	440x388x160.5
				Weight in kg	13.2



Design and specifications are subject to change by Marantz without notice.