


# marantz®



## SR7002 AV Receiver

The SR7002, 7x110W Current Feedback AV Receiver is THX Select2 certified, and is built to excel in both movie soundtrack and music reproduction. It supports all multi-channel audio formats including Dolby True HD and DTS HDMaster Audio for an impressive, all-encompassing 360-degree surround sound. And to ensure you get all of that full-blown experience, the Room Calibration by Audyssey MULT EQ automatically optimises the sound to your chosen room's unique interior. The M-DAX audio enhancer ensures compressed audio files such as MP3, AAC and WMA formats sound as good as CD. Quite simply, the clarity and dynamic range makes the SR7002 an excellent AV Receiver, fully in line with Marantz traditions.



because music matters

# marantz®



FEATURES	SR7002
<b>MULTICHANNEL SURROUND</b>	
THX Ultra II / Select II	-/o
THX Surround EX	o
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	o/o/o/o
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIX	o/o/o/o
7.1 PCM for HD-Audio from BluRay and HD-DVD	o
Circle Surround II / Neural Surround	o/o
Virtual Surround / Multichannel Stereo	o(Dolby VS)/o
HT-EQ / Re-EQ	-/o
Dolby Headphone / TruSurround Headphone	o/-
M-DAX Compressed audio Enhancer (MP3, WMA, ACC, iPod)	o
<b>SOUND ENHANCEMENTS</b>	
Current Feedback Topology	o
Pure Direct	o
Power Transformer: Toroidal / EI	-/o
High Grade Audio Components	o
Chassis: Copper plated / Metal	-/o

OTHERS	
Auto speaker setup by microphone	Audyssey MultEQ
Video conversion	CVBS < > S < > Comp >HDMI
Video scaling	-
Videoprocessing	-
T.B.C. - time base correction	o
Front panel cursor control	o
On Screen Display: GUI / OSD / multiroom OSD	-/o/o
Variable cross over	7
Lip sync control	o
Multiroom zones	1
Balanced in/out	-
Front Flap	o
Tuner	o
Auto TV Switching (On/Off)	o
Discrete RC coding (Main- / Multiroom)	o/o
RS232C (control / update)	o/o
<b>VIDEO</b>	
Composite In/Out	4/3
S-Video In/Out	4/3
Component In/Out	4/2
HDMI in/out (version x.x)	4/2 (1.3a)
HDMI V1.3 Deep Color pass through	o
Multi-Room Video Out: Video / S-Video / Component	o/-/-
<b>AUDIO</b>	
Analogue In/out	6/4
Digital Optical In/Out	3/1
Digital Coaxial In/Out	3/1
Digital audio by HDMI	o
Multi-Room Out: analog / digital	1/-
7.1ch Pre Out / Main In	o/-
7.1 multichannel input	o

OTHER	
Speaker Terminal: Gold plated screw / regular screw	-/o
Number of terminals	11
Speaker A/B	o
Bi-amp drive (5.1 ch setting) / Speaker C	o/o
Multi-Room Speaker Terminal	o
Multi-Room D.Bus	o
D.Bus	o
IR Receiver In / Emitter Out	-/-
IR Flasher In	1
RS232C	o
DC Triggers	2
Front Inputs: Audio / Composite / S-Video / Digital (Opt)	o/o/o/o
I-Pod input (direct / docking station)	-/o
USB Audio (MP3,AAC,WMA,WAV)	-

SPECIFICATIONS	
Power Output (8/6 Ohm RMS) (20Hz-20kHz 0.08%)	110/140 W
70% Guarantee	o
Audio Signal to Noise Ratio	105 dB
FM Tuner	o
Component video frequency response	5Hz to 80MHz (+-1dB)

GENERAL	
Available colors: Gold/Silver/Black/Silver-Gold	-/o/o/-
Metal Front Panel	o
System Remote Control	RC8001SR
Pre-programmed / Learnable / Touch Screen	o/o/-
Multiroom remote (included / optional)	RC101 (o/-)
Power Consumption in W	620
Standby Consumption in W (normal/economy mode)	1.0/0.7
Detachable Power Cable	o
Maximum Dimensions (W x D x H) in mm	440x396x184
Weight in kg	15.0



Design and specifications are subject to change by Marantz without notice.