


marantz®

NR1504

AV SURROUND RECEIVER



Slim-Line Home Theater Receiver with Advanced Network Capabilities

The Marantz NR1504 is a powerful 5-channel home theater receiver featuring high quality sound from a slim-line body and the addition of network capabilities that let you enjoy free internet radio as well as online streaming services such as Pandora, Spotify and SiriusXM. This receiver also supports AirPlay®, which lets you play a wide range of content from the music library in your iPhone®, iPod touch® and iPad®. With the Marantz Remote App you can easily operate the NR1504 from an Android or iOS device. The Setup Assistant displayed on your TV guides you through the quick and easy process of setting up your home theater. Once that's done, you're all set to enjoy all kinds of home theater entertainment along with an outstanding surround sound experience.

Marantz Audio Advantages

- 60 watts, 5 channel power (6 ohms, 1kHz, THD 0.7%)
- All-discrete, equal power, high current amplifiers
- High current linear power supply
- El core high current power transformer
- Pure Direct function
- M-DAX (Marantz Dynamic Audio eXpander)
- High resolution 192kHz/24-bit audio DACs

Audio/Video Quality

- Audyssey MultEQ, auto calibration w/microphone
- Audyssey Dynamic EQ
- Audyssey Dynamic Volume
- Supports 1080P and 3D video pass-through
- Network functions supporting playback of music files in high resolution formats (WAV 192 kHz/24 bit, FLAC 192 kHz/24 bit, ALAC 96 kHz/ 24 bit)
- Gapless audio playback

Connectivity

- Advanced network capabilities
 - AirPlay: stream music from your iPad, iPhone or iPod touch or from your iTunes® music library
 - Networking ready: stream internet radio, Pandora, SIRIUS XM, Spotify, as well as music and photos over the home network
 - Internet Radio
 - DLNA 1.5 certified
 - Photo streaming
 - flickr
- HDMI 6 in (front: 1) /1 out
- Supports HDMI (3D, ARC, Deep Color, "x.v.Color", Auto Lip Sync, and HDMI control function)
- Bluetooth wireless connectivity (M-XPort) via optional RX-101 adaptor
- Front panel USB input for direct digital playback for iPod, iPhone and USB drives
- 3/1 composite in/out
- 1/1 optical/coaxial digital in

- Headphone out
- FM/AM tuner
- 3 Audio inputs
- 1 Audio preout (Front L/R) and 1 subwoofer preout
- IR flasher in
- Remote control in/out

Ease of Use

- Mobile app control (Marantz Remote App) with advanced media browsing. (iOS & Android)
- Easy Setup Assistant with Graphical User Interface (GUI)
- Transparent binding-type speaker terminals for quick, easy connection of speaker cables
- New, visually clear layout on the rear panel that simplifies the connection of various cables
- Auto power off
- Standby source setting via HDMI control
- HDMI pass-through in standby mode

because music matters

Specifications

Audio Section

Power amplifier

Rated output:

Front:

- 50 W + 50 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.08 % T.H.D.)
- 60 W + 60 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)

Center:

- 50 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.08 % T.H.D.)
- 60 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)

Surround:

- 50 W + 50 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.08 % T.H.D.)
- 60 W + 60 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)

Analog

Input sensitivity/Input impedance:

130 mV/47 k Ω/ohms

Frequency response:

10 Hz – 100 kHz — +1, -3 dB (DIRECT mode)

S/N:

98 dB (IHF-A weighted, DIRECT mode)

Video Section

Standard video connectors

Input/output level and impedance:

1 Vp-p, 75 Ω/ohms

Frequency response:

5 Hz – 10 MHz — 0, -3 dB

Tuner Section [FM/AM]

(Note: μV at 75 Ω, 0 dBf = 1×10^{-15} W)

Receiving Range:

FM: 87.5 MHz – 107.9 MHz, AM: 520 kHz – 1710 kHz

Usable Sensitivity:

FM: 1.2 μV (12.8 dBf), AM: 18 μV

S/N:

MONO 70 dB (IHF-A weighted, DIRECT mode)

STEREO 67 dB (IHF-A weighted, DIRECT mode)

Total harmonic Distortion (at 1 kHz):

MONO 0.7 %

STEREO 1.0 %

General

Power supply:

AC 120 V, 60 Hz

Power consumption:

180 W

0.2 W (Standby)

0.5 W (CEC standby)

Dimensions (W x H x D):

17 21/64" x 4 9/64" x 14 29/64"

440 x 105 x 367 mm

Weight:

18 lbs 1 oz, 8.2 kg


Technology



PANDORA®



Made for



Fully discrete power amplifiers for all 5 channels




Convenient front panel HDMI input along with a USB port



Graphical User Interface allows easy setup and easy operation



AirPlay lets you stream audio content from your iPod, iPhone and iPad



New Marantz Remote App for iOS and Android devices



"Design and specifications are subject to change without notice. "Dolby" and the double-D symbol are trademarks of Dolby Laboratories. "DTS" is a registered trademark and the DTS logo, Symbol and DTS-HD are trademarks of DTS, Inc. "The terms HDMI and HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing LLC in the United States and other countries. "Windows Media and the Windows logo are trademarks or registered trademarks of Microsoft Corporation in the United States and/or other countries. "Made for iPod," and "Made for iPhone," mean that an electronic accessory has been designed to connect specifically to iPod, or iPhone, respectively, and has been certified by the developer to meet Apple performance standards. Apple is not responsible for the operation of this device or its compliance with safety and regulatory standards. Please note that the use of this accessory with iPod, iPhone, or iPad may affect wireless performance. AirPlay, iPad, iPhone, iPod, iPod touch, and iTunes are trademarks of Apple Inc., registered in the U.S. and other countries.

1-855-ONE-MARANTZ

1-855-663-6272

Call for Assistance: 9:00AM to 8:00PM M-F E.S.T.
For frequently asked questions please visit www.marantz.com

©2013 Marantz America, LLC.

For purposes of improvement, specifications and design are subject to change without notice. All specifications, dimensions and weights are subject to change without notice.

D&M Holdings, Marantz, Marantz America, LLC, or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors Being made by dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.