

marantz®



VS3003

3 in/1 out HDMI Switcher

The Marantz VS3003 HDMI Switcher allows up to three 8K devices to connect to select Marantz 8K AV receivers. Comes compact sized for easy placement and includes a handy remote control. Supports automatic power-on and input switching by HDMI CEC for ease of use. The VS3003 has detachable wall-mount brackets for custom integration and IR repeater capability if both the AVR and the Switcher are in a rack system or behind a cabinet blocking IR reception. The unique "AVR Control" feature allows changing the HDMI Switcher's inputs using the AVR's IR remote.

- **Connect Up to Three 8K Compatible Source Devices:** Prepare for the growing number of 8K or 4K/120Hz source devices by upgrading your beloved AV receiver with the Marantz VS3003. It allows up to three 8K devices to be connected to Marantz 8K AV receivers, tripling the input capability.
- **Compact Size and Elegant Look:** No bigger than a Blu-ray case in width and depth, the VS3003 can fit just about anywhere. It also features a premium look thanks to a brushed black Aluminum front plate.
- **Total Ease-of-Use:** Use HDMI-CEC to power on and switch inputs automatically on both the HDMI Switcher and the AV receiver. The unique "AVR Control" feature allows to switch the VS3003's inputs using the AVR's IR remote.
- **Custom-Install Friendly:** A detachable wall-mount bracket is included to allow mounting the HDMI Switcher on a wall. It also features wired IR remote repeater connectivity in case the VS3003 and AVR are in a rack system or behind a cabinet blocking IR reception.

Modern Musical Luxury



VS3003

Technical Specs

General	
Power Supply	AC 100–240V, 50/60Hz
Power Consumption	2.3W (Standby 0.2 W, CEC standby 0.5W)
Maximum Dimensions (W x H x D)	5.5 x 1.3 x 3.9in 140 x 34 x 98mm
Carton Dimensions (Packaging) (W x H x D)	11.2 x 2.7 x 10.8in 285 x 69 x 275mm
Weight	0.7 lbs / 0.3kg
Weight (with Packaging)	2 lbs / 0.9kg
Ports	
HDMI In	3x 8K / 40Gbps
HDMI Out	1x 8K / 40Gbps
Remote Control Flasher	1
Compatible Marantz 8K AV Receivers / Amplifiers	
AV8805A, AV7706, SR8015, SR7015, SR6015, SR5015, SR5015DAB, NR1711	

What's in the box	
HDMI switcher (VS3003)	1
Quick Start Guide	1
Safety Instructions	1
Cautions on Using Batteries	1
Remote control unit (RC046, with battery (CR2032))	1
HDMI cable (40 Gbps, approx. 1.5 m / 4'10")	1
Power supply cable (USB type, Approx. 1.5 m / 4'10")	1
AC adapter	1
AC adapter plugs (5 types)	5
Wall-mount bracket	1
Mounting screws (4 pieces)	4