

marantz®



CD 60

CD 60 CD Player

Extraordinary sound and peerless style—Marantz CD 60 celebrates your CD collection with a player engineered to sound better than any other in this class.

Built with high-quality materials and Sound Master tuned, CD 60 adds precision CD playback to MODEL 40n or any high-quality audio system.

- Hyper Dynamic Amplifier Modules
- Optimized HDAM Circuit
- High-Current Power Supply
- Plays Hi-Res Audio USB Sources
- Reference-Quality Digital-to-Analogue Conversion
- Customizable Digital Filter
- High-Performance Headphone Amplifier
- Full-System Remote Control
- Tuned with Passion



The Most Musical Sound

CD 60

Technical Specifications



Features	
CD Compatibility: CD / CD-R/RW / SA-CD / WMA / MP3 / AAC	• / • / - / • / • / - /
CD-Text / SA-CD Text / ID3 Tag / WMA Meta Tag / AAC Meta data	- / - / • / • / • / •
HDAM version	HDAM+HDAM SA2
Power Transformer: Toroidal / EI	- / •
High Grade Audio Components	•
Customised Components	•
Symmetric circuit layout	•
Copper plated chassis	-
Extra metal plate for chassis strengthening	•
Digital out off / Audio EX Mode	• / -
Headphone: Standard / Buffer / Current feedback	- / • (HDAM-SA2) / -
Other	
Selectable filter: CD / SA-CD / DAC-Mode	• / - / -
Marantz Musical Mastering	•
Separated rectifier circuit for analogue and digital circuitry	•
Display: Dimmer / Off	• / •
Playback	
Program Play (CD)	25
Repeat	•
Random Play	•
Inputs / Outputs	
Analogue Out (Cinch)	2ch
Balanced Out	-
Digital Optical In / Out	- / 1
Digital Coaxial In / Out	- / 1
Gold plated Cinch	•
USB Audio (front) / Made for iPod / Made for iPhone	• / - / -
USB-A: FLAC / WAV / AIFF / ALAC / DSD	•
D-Bus	•
Headphone Out	•
Headphone Volume Control	•

Specifications	
Mechanism	JTL-101Y
D/A Conversion	Multi-bit, Delta-Sigma
DAC IC	ES9016K2M
Digital Filter	ES9016K2M
Noise Shaper	ES9016K2M
Low Pass Filter stage	HDAM (new)
Output Buffer	HDAM SA2
Headphone amp	HDAM-SA2buffer+OPAMP
CDDA AUDIO	
Frequency Response	2 Hz - 20 kHz
Dynamic Range	100 dB
Signal to Noise Ratio	110 dB
Total Harmonic Distortion	0.002%
Channel Separation	98 dB
General	
Available colors: Gold / Silver / Black / Silver-Gold	- / - / • / •
Metal Front Panel	•
Remote Control	RC005PMCD
Power Consumption in W	46
Standby Consumption in W	0.3
Auto power off	•
Detachable Power Cable	•
Maximum Dimensions (W x H x D) in cm	442 x 129 x 396mm
Weight in kg	8.0kg
Carton Maximum Dimensions (W x H x D) in cm	525 x 249 x 511mm
Carton Weight (incl. product) in kg	10.2kg
EAN	
SAP code / EAN BLACK	CD60/N1B 0747192136499
SAP code / EAN SILVER-GOLD	CD60/N1SG 0747192136505



IEC60825-1:2014

Design and specifications are subject to change by Marantz without notice.

www.marantz.com

